
CXP-HOG SERIES MANUAL & BEAGAME CHANGER ICS AIRSOFT



CXP-HOG SERIES MANUAL





Patents acquired: US7077117B1 / USD706879S / USD706880S / R.O.C. M244431 / R.O.C. M320468 / R.O.C. D160112 / R.O.C. D159178 / EM002246579-0001



電槍使用之注意事項 Maintenance

- 2. 一旦發生卡彈或射擊速度降低時,應立即停止射擊, 以避免齒輪過度耗損。請使用通槍條將殘彈清除,或 檢測雷池雷量後方可繼續使用。
- 3. 不使用本產品時,請務必將射擊選擇鈕置於保險(S)的 3. Plei 位置上,將電池移除並定期使用通槍條清潔槍管。
- 4. 請依原廠附贈之保險絲規格使用。不當配置可能導
- M120彈籌請用25A保險絲。 5. 彈頭直徑6mm。其槍口動能為二焦耳以下、射程範圍
- 為50公尺以內。 6. 適用年齡為18歲以上。
- 7. 使用本商品不得改造或變造,並不得使用金屬彈頭。
- 睛。使用時應確保本身及射程範圍內所有人員均已確 實穿戴護日鏡。 9. 使用方法及注意事項請詳閱説明書內容。
- 10. 建議使用以下電池以達到最大效益:
- SSS系統建議使用7 4v & 11 1v Li-Po雷池。 傳統電閘與FET電閘系統11.1v LiPo電池Ready。 ※使用非建議電池可能會造成產品效能低落、功能異
- 常甚至損毀。 (原產地:台灣/製造商:一芝軒企業有限公司/地址: 台中市神岡區東洲路79巷67號 / 電話: 04-25256461)

- 1. 請勿使用劣質或回收BB彈,以減少槍管損耗及避免卡 1. To reduce the abrasion of inner barrel and to avoid BB jam, please do not use inferior or reused BB pellets.

 2. If your gun is jammed or the muzzle velocity has decreased, please stop shooting immediately in case the gear abrades excessively. Use the
 - clearing rod to clear out the remaining pellets, or check your battery power before continue using your gun.
 - 3. Please engage the safety, dismount the battery and clear the inner barrel with the clearing rod periodically when not using this product.

 4. Please use the same fuse specification as the original one. Equipping improper fuse might cause malfunction to the components. Apply 20A
 - fuse if the gun using a M100 spring; apply 25A fuse if using M120 spring. The diameter of the BB pellet is 6mm. The muzzle energy is less than two joules, and the shooting range is within 50 meters.
 - 6. The recommended age to operate this product is 18 years old and above. 7. Modify, reform, and using metal bullets on this product are strictly
- 18. 「此槍非玩具」,濫用可能造成嚴重傷害,尤其是眼 8. This is NOT a toy. Abusing might cause severe injuries, especially to the eyes. Before operating, please make sure that every personnel in the shooting range have worn eye protections properly, including the operator. 9. Please read the manual for instruction and precaution.
 - 10. In order to achieve the maximum performance, the following batteries are
 - SSS system: 7.4v or 11.1v Li-Po batteries
 - Traditional switch and FET switch system: 11.1v Li-Po battery Ready. **Using non-recommended batteries may cause poor performance, abnormal functions or even damage to the product.
 - Origin: Taiwan/ Manufacturer: ICS enterprise Co., Ltd / Address: No.67, Ln. 79, Dongzhou Rd., Shengang Dist., Taichung City 429, Taiwan / TEL: (+886) 4-2525-6461





各部名稱 Series Component





















相關系列產品型號與詳細規格,請以官方網站公布為主。 For related series product models and detailed specifications, please refer to the official website.








可動部的說明 Movable Parts

槍身結合3號齒正確位置圖

The correct position of sector gear before reassembling

注意 未進行歸位校正,會損壞活塞及齒輪

 $\ensuremath{\mathbb{X}}$ The piston and gear may be damaged without correcting the position in advance.



號齒在槍身結合時,必須轉到正確位置, 上可將上槍身蓋下。

Make sure the sector gear is turned to the correct position before reassembling the

3-2 快拆尾頂桿 QD Spring Guide

- 1.使用4mm六角板手,對準尾頂桿往內推入後旋轉45度
- 2.將尾頂桿與彈簧抽出
- ※安裝彈簧後依照步驟1倒序組裝
- 1. Use 4mm Allen key, insert it to the spring guide and then press down to turn 45 degrees.
- 2. Take out the spring guide and spring.







精確射擊調整動作 Precision Targeting Adjustment

準星覘孔調整方式 Front and Rear Sight Adjustment


A: 彈跳式準星覘孔 Back-up front and rear sights






4-2 選擇射擊模式 Shooting Mode Setting

1 保險 Safe









- ※此系列產品具備 「關保險自動釋放彈簧功能」
- 1.槍上有彈匣的情況下,關保險會自動釋放彈簧,有機率造成第一發雙彈射出或者小便彈,屬正常情況。
- 2. 槍枝使用完畢,請轉至單發模式下,擊發2~3下後做清槍動作,再關保險確保槍管內已無殘彈。
- 3. 上下槍身分解前,務必先關保險釋放彈簧,避免造成齒輪倒轉損壞活塞。
- ※關保險自動釋放,可延長彈簧壽命,避免長期擠壓造成疲乏
- * This product is equipped with an auto spring tension releases mechanism in the safety mode.
- 1. Having a magazine loaded, it is a normal condition that the gun might shoot a double shot, or a weak shot after turning it to safety and releasing the tension stored in the spring.
- 2. After finishing playing, fire the gun 2-3 times in semi auto to clear the remaining BBs inside the hop-up chamber, then switch the selector lever to safety to ensure there is no BB left inside.
- 3. Before opening the upper and lower receivers, always release the spring tension by turning the selector lever to safety position, this will avoid spring damage from sudden release from the sector gear.
- * The spring tension release mechanism can extend the spring lifetime by avoiding spring fatigued from long time

B: 準星高度調整 Front sight adjustment



將調整扭轉左即可升高準星;將調整扭轉右即可降低準星 Rotate the dial counterclockwise to raise the aiming point. Rotate clockwise to lower the aiming point.

C: 瞄準距離遠近調整 Aiming distance adjustment



近距:將覘孔往前推 For close range, flip sight forward.



遠距:將覘孔往後推 For far range, flip sight backward.

D: 覘孔左右調整 Rear sight windage adjustment




依旋鈕方向旋轉即可將覘孔組左右調整 Rotate clockwise to aim right. Rotate counter clockwise to aim left


H-UP 彈道調整

↑ 注意 非必要時,手指請勿放置於H-UP調整處,避免受傷

*To avoid injuries, only put your finger on the H-up adjustment when necessary.




- 1.將槍機拉柄往後拉(不可放開),防塵蓋下翻、槍機飾片向後打開, 即可進行彈道調整。 2. 視彈道進行撥盤調整,調整完即可放開槍機拉柄。
- 1. To adjust the trajectory, pull and hold the charging handle to the end (do not release) to open the ejection port cover downward, and open the decorated bolt plate backward.
- 2. Rotate the dial to adjust the trajectory. Release the charging handle once you finished the adjustment.



H-UP調整:BB彈呈現一直線的彈道才是正確射法。 過於上飄:將撥片往前推。

過於下墜:將撥片往後拉。

H-up Adjustment: Make sure the trajectory of the BB pellets to be straight. When the BB pellet flies up: Push the H-UP lever forward to lower the trajectory When the BB pellet falls down: Push the H-UP lever backward to raise the trajectory.



6-2 電池裝卸方式 Loading the battery

A: MTR 托 MTR Stock

2

2.將馬達拆下

3.取下保險絲


1.旋開握把底蓋螺絲並卸下握把底蓋

4. 拆解槍托擋塊與托桿下蓋螺絲

5.拆解槍托固定桿螺絲取下托桿

將槍托調整桿往下拉並轉向側邊,向後取下槍托, 方便安裝電池。

Pull the stock adjustment lever downward and turn it to aside. The battery can be loaded with ease after you remove the stock backward.




B:MTR S1 托 MTR S1 Stock

按下壓鈕即可分離槍托底蓋,方便安裝電池。 Press the button on the top of the stock to remove the butt cap and for easy battery installation.



c: UKSR 托 **UKSR Stock**

用硬幣即可輕鬆解鎖取下槍托底蓋,方便安裝電池。 You can unscrew and remove the stock butt cap with a coin easily for easy battery installation.



齒輪箱拆解 Disassemble Gearbox 注意 先卸彈匣跟電池,再進行拆解

****Unload the magazine and battery before you proceed to disassemble.**

1. Unscrew and remove the pistol grip butt cap.


4. Remove the tube rubber block and tube lower

5. Release the tube screw then remove the tube.


2. Take the motor out.

3. Remove the fuse.

cover screw.







1.旋開線槽螺絲 2.旋開彈匣卡榫螺絲並取下。

3.將下齒輪箱取出

1. Release the screw on wire guard assembly

2. Remove the screw on the magazine catch button

3. Take out the lower gearbox.